

Steps to Reinstall **BDE** on a Workstation

Remove **BDE**

- Open the Windows Explorer locate the following folders:
- Delete the Idapi folder.
C:\Idapi
- Delete the Borland folder.
C:\Program Files\Borland
C:\Program Files\Common Files\Borland Shared.

Remove other versions of **BDE**.

- Click **Start; Find; Files or Folders**.
Under Named type, **Idapi***
Search the local drives.
- Remove any Idapi folders found. (Commonly under Corel/Shared/ if using Wordperfect)

Note: If you cannot remove all Borland files because they are in use, remove all files possible & any registry keys. Restart the workstation and delete the rest of the files.

Remove **BDE** Registry Keys

- Click **Start; Run** Type in **REGEDIT** and press **Enter**.
- Make a [backup of the registry](#)
- Click **h_key_curent_user; Software**
Delete **Borland**
- Click **h_key_local_machine; Software**
Delete **Borland**
- Close the registry editor.

Reinstall **BDE**:

- Place the Timeslips CD in the CD-Rom drive.
- Exit the Timeslips installer.
- Click on **Start; Run; Browse**.
- Locate the CD-Rom drive.
- Open the **Timeslip** folder.
- Open the **Bde32** folder*.
- Click on the **Setup.exe** and click **Open**.
- Click **OK** to run the install.

After installing, open Timeslips.

*****NOTE:** You do not need to reinstall BDE16 unless you are converting data or interfacing with an application that uses the 16-bit **BDE** link.